




**Purpose: To configure the Local Web Server to use the PMS/Access Code Portal Template.**

This document will instruct you how to configure the Local Web Server pages to use the PMS/Access Code Portal Template. **NOTE:** Please download the PMSAccessCodeLogin.zip file and unzip the contents before proceeding.

**Important Note:** This template supports one PMS billing option with a time unit of 1. The PMS selected must be a two-way system, which uses the last name and room number for verification and billing.

1. **FTP the Portal Files to the AG.** Log into the AG using FTP.



Change to the web directory upload the pms-accesscodelogin.htm file to the web directory and create two directories: css and images.



FTP the pms-accesscodelogin.css to the web\css directory and the loginBackground.jpg and loginLogo.png to the web\images directory



2. **Configure the Local Web Server settings.** Login to the Nomadix Web Management Interface (WMI) and add the Local Web Server pages to the configuration (Subscriber Interface->Local Web Server). Add each page and image under the appropriate section.

**Local Web Server Setup**

**Notes:**

1. Limit the total size of Web Pages and Images to 1000 KB.
2. The Pre-Authentication Pages and Images are available at <http://nseip:1111/web/<filename>> or at <https://nseip:1112/web/<filename>>
3. The Post-Authentication Pages and Images are available at <http://nseip:3111/web/<filename>>

Web Page File Name:

Web Page File Name:

Image File Name:

Image File Name:

Click on the Reread Files button after all pages and images added

3. **Configure the Portal Page.** Under Configuration->AAA, Enable AAA, then select the Internal Web Server tab, Enable New Subscribers and Enable Portal Page with Portal Page URL pointing to the PMS Portal Template. <http://login.nomadix.com:1111/web/pms-accesscodelogin.htm>

Options Internal Web Server External Web Server

SSL Support  Enabled ⓘ

Encrypt only Sensitive Data  Enabled

Certificate DNS Name

Enable

Portal Page URL  ⚠ Caution

Parameter Passing  Enabled

Parameter Signing:

Click on the Save button to apply the changes.



4. **Configure Billing Plan.** When using the PMS/Access Code Portal Template, only Billing Plan 0 will be used, all others will be ignored.

**Note:** An X over Y billing plan is not supported at this time

Under Subscriber Interface/Billing Options select Plan 0 and configure the billing plan as needed. If you want the plan to be used and a 0.00 post charged to the PMS, then set the value for the time increment to 0.00. If you want the PMS to validate the guest credentials, without posting a charge, select the Free For PMS User option.

If you want the plan to charge for this plan, enter in the desired charge. When this is selected, the subscriber will be billed for 1 unit of the selected time. For example, if the plan is set for 5.95 for the hourly rate, the user will be charge 5.95 and gain one hour of access.

5. **Create Access Code** Go to Subscriber Administration/Access codes to create a code.

The screenshot shows a web interface for managing access codes. At the top, there's a header 'Access Codes' with a sub-header 'Manage plans for creating guest Internet access codes'. Below this is a navigation bar with four tabs: 'Available Plans', 'Edit Plans', 'General Setup', and 'Reprint Tickets'. The 'Available Plans' section is active, showing a table with columns: Plan Name, Session Time, Start Using By, # Uses, Code Example, BW Upstrm, BW Dnstrm, BW Class, and QoS Policy. The table is currently empty, and a message at the bottom states: 'There are no Plans to view. Click [Add icon] to create a new plan.'

Select Edit Plans to create a new plan and enter in the parameters you want for the plan. Click Add to create.



**Access Codes**  
Manage plans for creating guest Internet access codes

Available Plans | Edit Plans | Reprint

Add or Edit a Plan  
Please allow pop-ups for printing.

Plan Name: 1 Hour  
Maximum Devices: 1  
DHCP Type: Private  
BW Upstream: 1024 kbps  
BW Class:  
Batch Print: 1

Access Codes: 123 - nnnn-nn digits - Suffix  
Session Time: 0 wks/ 0 days/ 1 hrs/ 0 mins  
Activate By: 2019-06-30 12:00 PM  
DHCP Subnet: 0.0.0.0  
BW Downstream: 1024 kbps  
QoS Policy:

+ Add | Save | Create & Print | Restore

You will need to click on Create & Print to generate the code to be used.

Print

— Internet Access Code —

**123-3062-91**

This Internet Access Code is valid for 1 hour and 1 device, must be activated before 12:00 pm, 2019-06-30.



6. **Enable Suppress posting of zero payment.** Under Configuration/PMS, scroll down to the Miscellaneous settings section and enable This option.

**Miscellaneous settings:**

<input type="checkbox"/>	Phonetic name matching (applies to WFB, FOSSE, Micros and Micros Fidelio only) <a href="#">Phonetic test</a>
<input type="checkbox"/>	Syslog PMS communications (applies to WFB and FOSSE only)
<input type="checkbox"/>	Post to folio with CA (cash) method of payment (applies to WFB and FOSSE only)
<input checked="" type="checkbox"/>	Post to folio with SC (sign charges) method of payment (applies to WFB and FOSSE only)
<input checked="" type="checkbox"/>	Suppress posting of zero payment amount (applies to Micros and Micros Fidelio only)

7. **User Experience** When the subscribe launches their browser, they will be presented with the following web page. Here they will enter in their Room Number and Last Name or their Access Code and select Sign In to gain access.





## How to customize the portal page.

With this portal page you can change the Logo Placement image, the background image and the wording. This can be done by editing the pms-accesscode/login.htm file.

The easiest way to replace the images is to create new ones, with the same name and overwrite them in the images directory. This way you will not need to edit the page if you only want to change the images.

loginLogo.png is the Logo Placement image  
loginBackground.jpg is the background image

If you wish to use your own images without renaming them, you will need to upload the new images to the /web/images directory and then edit the page and enter the new names in the following sections.

For the Logo Placement image, replace loginLogo.png with the new image name

```
<div id="logo">  
      
</div>
```

If you want to Change Room Number and/or Last Name, you will replace Room number and Last Name in the fields below.

```
<form class="nse-form-style" onsubmit="return NSE.pmsPurchase(this);">  
    <input type="text" name="pmsroom" placeholder="Room number" >  
    <input type="text" name="pmsname" placeholder="Last Name" >
```

For the background image, you will need to edit the pms-login.css and replace loginBackground.jpg with the new image name

```
body {  
    font: Arial, Helvetica, sans-serif;  
    position: relative;  
    background-image: url(../images/loginBackground.jpg);  
    background-repeat: no-repeat;  
    background-position: center center;  
    background-size: cover;  
}
```

How to use the PMS-Access Code Portal Template